

DATA SHEET

The AccessPad from Sera4® is designed to be mounted on the outside of cabinets and shelters controlled by a Sera4 lock controller. It brings the following features to an easily accessible point on the outside of the cabinet:

- **External 9V battery terminal:** used in emergencies to ensure the access system works even if all other sources of power are not active.
- **Button:** enables controller wakeup for installations that are powered only by battery.
- **LED Indicator:** shows controller status and enables Failsafe Unlock, for audit-compliant opens without a smartphone.

Features

- 9V backup battery terminal w/boost for 12V/0.5A locks
- Button with LED power indicator
- Quick and easy to install
- 1-cable connection to a Sera4 lock controller
- Outdoor design for extreme weather

Installation Guide

AP-N-002-EN.pdf can be downloaded from <https://support.sera.com>



Dimension	A	B	C
Size (mm)	40	60	25

Sera4 Controller	Part Number
X-Series	AX5-AP
SLC2	SLC2-AP

Parameter	Certification / Characteristic
Water & Dust Resistance Rating	IP65-compliant
Operating Temperature	-40°C to 85°C
Case	Corrosion-resistant polycarbonate and SS316 stainless steel
Indicator Light	High-visibility LED
Button	Single button for wake and Failsafe Unlock code entry
Power	Powered by Sera4 lock controller; provides 9V battery terminal
Included Cable Length	610 mm / 24 inches

*Sera4, Teleporte, Unlock Controller, and the Sera4 logo are trademarks of Sera4 Ltd.
For more information on Sera4 and the Teleporte service, visit <http://www.sera4.com>*